

## CLAIMS:

1. A digital signal processing integrated circuit, comprising
  - an array of interconnected and programmed or programmable digital signal processors (10), at least some of the digital signal processors (10) having IO ports;
  - an IO connection (11a,b) for communicating a signal stream between signal  
5 processors (10) in the array and circuitry outside the array;
  - a configurable multiplexing circuit (12), between the IO connection (11a,b) and the IO ports of at least a plurality of the digital signal processors (10), the multiplexing circuit (12) being configurable under control of configuration data, the multiplexing circuit (12) being arranged to give the effect of accessing the IO connection only to IO signals from  
10 the IO port or ports of one or ones of the respective plurality of digital signal processors (10) that are selected by the configuration data.
2. A digital signal processing integrated circuit according to claim 1, wherein the multiplexing circuit (12) is arranged to give unconditional, arbitration free access from the IO  
15 port of the selected one or ones of the plurality of digital signal processors (10) to the IO connection (11a).
3. A digital signal processing integrated circuit according to claim 1, comprising a plurality of IO connections (11a,b) including said IO connection (11a,b) and a plurality of  
20 configurable multiplexing circuits (12) including said configurable multiplexing circuit, each configurable multiplexing circuit (12) coupling a respective IO connection (11a,b) to IO ports of at least a respective plurality of the digital signal processors (10), each multiplexing circuit (12) being configurable under control of configuration data, and each multiplexing circuit (12) being arranged to give the effect of accessing the IO connection (11a,b) only to IO  
25 signals from the IO port or ports of one or ones of the respective plurality of digital signal processors (10) that are selected by the configuration data for that multiplexing circuit, the IO port of at least one of the digital signal processors (10) being coupled in common to a plurality of the multiplexing circuits (12), separately from the IO ports of other digital signal processors (10).

4. A digital signal processing integrated circuit according to claim 1, comprising a peripheral circuit (14), coupled to a respective one of the IO connections (11a,b), the peripheral circuit (14) having a control input, the peripheral circuit (14) being responsive to  
5 respective control signal values at the control input, the multiplexing circuit (12) associating each control signal value with a respective IO signal value selected under control of the configuration data, the multiplexing circuit (12) being arranged to translate the IO signals from the IO ports of the selected one or ones of the digital signal processors (10) into  
10 respective control signal values associated with the IO signal values, for supply to the peripheral circuit.

5. A digital signal processing integrated circuit according to claim 4, wherein the multiplexing circuit (12) is arranged to associate a control signal value with respective, independently configurable IO signal values from different ones of the respective digital  
15 signal processors (10) respectively.

6. A digital signal processing integrated circuit according to claim 1, wherein the digital signal processors (10) are arranged to execute IO instructions that specify an IO address, the IO ports (25) having address lines for outputting the IO address, the multiplexing  
20 circuit (12) being arranged to configurably associate each selected digital signal processor (10) that is connected to the multiplexing circuit (12) to a respective configurable IO address value, the multiplexing circuit (12) being arranged to enable transport of data between the respective connection and the IO port (25) of a particular one of the digital signal processors in response to receiving, from the IO port (25) of that particular one of the signal processing  
25 circuits, the IO address value that is configurably associated with that particular one of the signal processing circuits (10).

7. A digital signal processing integrated circuit according to claim 4, wherein the multiplexing circuit comprises  
30 - a plurality of configuration data storage elements (60);  
- a plurality of comparators (62), each comparator (62) having a first input coupled to a respective one of the configuration data storage elements (60) and a second input coupled to the IO port (25) of a respective one of the digital signal processors (10) for receiving IO addresses;

- a control signal generating circuit (64), having inputs coupled to outputs of the comparators (62), and arranged to enable transport of data between the IO connection and the IO port (25) of those digital signal processors (10) for which the comparators indicate a match.

5

8. A digital signal processing integrated circuit according to claim 1, wherein the configuration data in the multiplexing circuits (12) is programmable under control of signals from the IO ports of the digital signal processors (10).

10 9. A digital signal processing integrated circuit according to claim 1, wherein the digital signal processors (10) are programmed to perform a signal processing operation that comprises a plurality of tasks, each task executed by a respective one of the digital signal processors (10), the integrated circuit comprising neighbor interconnections between digital signal processing circuits (10) in the array, in which signal processing operation signal  
15 streams flow between respective tasks via the interconnections and to front end and/or from back end tasks of said tasks from and to the IO connections (11a,b) respectively, and wherein the digital signal processing integrated circuit is programmed to establish a configuration wherein the multiplexing circuits (12) are configured so that only IO signals from the IO ports of one or ones of the respective plurality of digital signal processors (10) that execute  
20 the front end and/or back end tasks have the effect of accessing the respective IO connections.

10. A digital signal processing integrated circuit according to claim 9, wherein each particular digital signal processor (10) that executes a particular front end and/or back  
25 end task is programmed to write the configuration data to the multiplexing circuits to establish a configuration wherein the multiplexing circuits access the IO connection (11a,b) with which the front end and/or back end task exchanges the signal streams in response to IO signals from that particular digital signal processor (10).

30 11. A method of executing a signal processing operation that inputs and/or outputs a stream of signal data, the method comprising the steps of  
- executing different tasks that are part of the signal processing operation by executing respective programs in respective digital signal processors (10) in an integrated circuit, communicating intermediate streams of data between tasks in different digital signal

processors (10), the digital signal processors (10) including a particular digital signal processor (10) that executes a front end and/or back end task that contains an IO instruction for receiving and/or transmitting signals from an external stream of signal data;

- prior to said executing, programming configuration data of a multiplexing

- 5 circuit (12) that is coupled between an IO connection and IO ports of at least a plurality of the digital signal processors (10), the configuration data controlling the multiplexing circuit (12) to give the effect of accessing the respective IO connection (11a,b) only to IO signals from the IO port of the particular digital signal processors (10) that are selected by the configuration data.

10

12. A method according to Claim 11, wherein a switch between programmed signal processing operation is executed, the switch comprising reprogramming the configuration data, so that mutually different ones of the digital signal processors (10) execute the front end and/or back end task before and after the switch.

15

13. A computer program product with instructions for executing a signal processing operation that inputs and/or outputs a stream of signal data, the instructions comprising instruction for executing the steps of

- executing different tasks that are part of the signal processing operation by

- 20 executing respective programs in respective digital signal processors (10) in an integrated circuit, communicating intermediate streams of data between tasks in different digital signal processors (10), the digital signal processors (10) including a particular digital signal processor (10) that executes a front end and/or back end task that contains an IO instruction for receiving and/or transmitting signals from an external stream of signal data;

- 25 - prior to said executing, programming configuration data of a multiplexing circuit (12) that is coupled between an IO connection (11a,b) and IO ports of at least a plurality of the digital signal processors (10), the configuration data controlling the multiplexing circuit (12) to give the effect of accessing the respective IO connection only to IO signals from the IO port of the particular digital signal processors (10) that are selected by  
30 the configuration data.